

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
1 April 2004 (01.04.2004)


PCT

(10) International Publication Number
WO 2004/028030 A1

- (51) International Patent Classification⁷: H04B 7/005 (72) Inventors; and
(75) Inventors/Applicants (*for US only*): NILSSON, Johan [SE/SE]; Trulsibrunnsvägen 20 A, S-236 38 Höllviken (SE). BERNHARDSSON, Bo [SE/SE]; Spjutgränden 5, S-224 75 Lund (SE).
- (21) International Application Number: PCT/EP2003/009781
- (22) International Filing Date: 3 September 2003 (03.09.2003) (74) Agent: O'CONNELL, David, Christopher; Haseltine Lake, Imperial House, 15-19 Kingsway, London WC2B 6UD (GB).
- (25) Filing Language: English
- (26) Publication Language: English
- (30) Priority Data:
02256578.2 23 September 2002 (23.09.2002) EP
60/414,082 26 September 2002 (26.09.2002) US
- (81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.
- (71) Applicant (*for all designated States except US*): TELEFONAKTIEBOLAGET L M ERICSSON (publ) [SE/SE]; S-126 25 Stockholm (SE). (84) Designated States (*regional*): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW),

[Continued on next page]

(54) Title: METHOD AND APPARATUS FOR POWER CONTROL IN A MOBILE RADIO SYSTEM



(57) Abstract: A telecommunications system for improving quality of service (QoS) to users via the implementation of an extended outer loop power control algorithm. A radio resource manager (RRM) operates to determine the number of channels allotted to users within a network at a certain time. The RRM implements the extended outer loop power control algorithm for each allotted channel, thus determining SIR reference values for each allotted channel. the RRM ensures that the SIR reference value for any channel does not fall below a predetermined minimum value. The SIR reference value to be used for all channels in use is determined as the highest of all the calculated SIR reference values. The extended outer loop power control algorithm can be implemented at a mobile station level, base station level or radio network controller level.

WO 2004/028030 A1



Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM),
European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE,
ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO,
SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM,
GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

Published:

— with international search report

METHOD AND APPARATUS FOR POWER CONTROL IN A MOBILE RADIO SYSTEM

Technical Field of the Invention

5 The present invention relates to power control in Radio Resource Management, and in particular to a system with multiple transport channels.

Description of Related Art

10

In modern telecommunications networks, the utilisation of air interface resources and the maintenance of Quality of Service (QoS) is determined by Radio Resource Management (RRM). RRM is responsible for the following functions;

15 handover, power control, admission control, load control and packet scheduling. Each of these functions is implemented by a relevant RRM algorithm.

Third generation telecommunications networks need to
20 support high quality services and to multiplex several services on one connection. In particular, power control plays an important role in the provision of the required QoS, by keeping the interference levels in the air interface at a minimum. The power control algorithm may
25 be implemented at User Equipment (UE) level, Base Station (BS) level or Radio Network Controller (RNC) level. These three network elements are illustrated in Figure 1, wherein the BS 10 includes a transceiver 12 and a processor 14, which processor 14 has a fixed connection
30 to the RNC 16. The MS 18 is not generally of a fixed location.

Aspects of power control which are specific to third generation systems (such as Wideband Code Division
35 Multiple Access, WCDMA) and are not present in second generation systems (such as Global System for Mobile

Communications, GSM) include fast power control and outer loop power control. Fast power control in WCDMA has a frequency of approximately 1.5kHz and is supported in both uplink and downlink. The outer loop power control algorithm estimates the received signal quality in order to adjust the Signal to Interference Ratio (SIR) reference for the fast power control so that the required QoS is maintained. Signal quality can be affected by changes in the MS speed or the multipath propagation environment. Outer loop power control in WCDMA has a frequency of approximately 10-100Hz, and is needed in both uplink and downlink because there is fast power control in both uplink and downlink.

Fig 2 is a flow chart outlining a general outer loop power control algorithm. An initial assessment is made as to whether the quality of signal received on the uplink is better than the required quality of signal. Where this is the case, the SIR reference for fast power control is decreased to avoid wasted network capacity. In contrast, where the quality of signal is less than the required quality, the SIR reference is increased so that the required QoS is maintained.

QoS is a direct function of errors arising from the received signals, which errors arise from inaccurate SIR estimation, signalling errors and delays in the power control loop. In order to assess the quality of signal received on the uplink, several known methods can be employed. For example, the quality assessment can be based on an estimated physical channel Bit Error Rate (BER), received SIR or a Cyclic Redundancy Check (CRC).

The CRC assessment is generally utilised for network services where errors are allowed to occur fairly frequently, at least once every few seconds. This can be

in non-real-time packet data service where the block error rate (BLER) can be up to 10-20% before retransmissions, and the speech service where typically BLER = 1% provides the required quality.

5

One possible outer loop power control algorithm is given by the so-called proportional-integral (PI) algorithm. This can be characterised as follows:

$$10 \quad SIR_r(k) = kp * e(k) + ki * I(k)$$

where k denotes block number, $SIR_r(k)$ denotes the SIR reference for block k , kp and ki are parameters which control algorithm convergence speed and stability, $e(k)$ is a variable which indicates the difference between required QoS and actual QoS, and $I(k)$ is a parameter which sets a steady state value for the SIR reference, where $I(k + 1) = I(k) + e(k)$. For example one could use;

$$20 \quad \begin{array}{ll} e(k) = -BLER_r, & \text{if CRC ok,} \\ e(k) = 1 - BLER_r, & \text{if CRC not ok} \end{array}$$

where $BLER_r$ refers to the BLER reference. It is also possible to filter $e(k)$ to get a smoother behaviour. Examples of values of the constants kp and ki are $kp = 0.3$ and $ki = 0.8$. A special case is given by the parameter choice:

$$\begin{array}{l} kp = 0 \\ ki = SIR_{inc} / (1 - BLER_r) \end{array}$$

30 which gives the so-called jump algorithm disclosed in "WCDMA for UMTS" edited by Holma and Toskala, Wiley & Sons Ltd, 2000, pages 187 - 203. This jump algorithm is based on the result of a CRC assessment of the data and can be characterised as follows:

35

$$SIR_r(k+1) := \begin{cases} SIR_r(k) + SIR_{inc} & \text{if CRC not OK,} \\ SIR_r(k) - \frac{BLER_r}{1-BLER_r} SIR_{inc} & \text{if CRC OK.} \end{cases}$$

where SIR_{inc} refers to an incremental increase in the SIR
 5 reference for the channel under consideration. SIR_{inc} is
 typically 0.3dB to 1.0dB.

Both the PI algorithm and the jump algorithm calculate an
 updated SIR reference value based on the value of the
 10 previous SIR reference value. Where the received signal
 quality is better than the required signal quality, then
 the updated SIR reference value will be an incremental
 decrease. Where the received signal quality is worse
 than the required signal quality, then the updated SIR
 15 reference value will be an incremental increase.

In order to make efficient use of network capacity, the
 outer loop power control should keep the SIR reference as
 low as possible at all times. Although, an SIR reference
 20 value that is too low will lead to decreased QoS. The
 data traffic situation can vary over time and so a
 flexible and reliable system is required to ensure that
 users experience an acceptable QoS.

25 This known power control function does not enable a
 suitable SIR reference to be determined where multiple
 transport channels are used. When multiple transport
 channels are multiplexed on a physical channel a common
 SIR reference must be found which gives sufficiently good
 30 performance for all transport channels. The necessary
 SIR level is a complicated function of coding scheme,
 channel quality, equipment velocity and other parameters
 and can not be calculated easily. The number of possible
 combinations of transport channels is also very large
 35 which makes utilisation of a look-up table unfeasible.

Summary

The present invention seeks to provide a power control function in RRM in which the required QoS is maintained for multiple transport channels and problems in known systems associated with data traffic changes are alleviated.

According to a first aspect of the present invention, there is provided a method of power control in a mobile telecommunications network, the method comprising the steps of calculating a signal strength reference value for each of a plurality of channels in use based on a previously calculated value for that channel, maintaining the calculated signal strength reference value for a channel at or above a predetermined minimum signal strength reference value, and determining a signal strength reference value to be used for all of said plurality of channels in use, as the highest of all of the calculated signal strength reference values.

According to a second aspect of the present invention, there is provided a mobile station in a telecommunications network, wherein the mobile station comprises means for performing power control by the method specified in the first aspect of the present invention.

According to a third aspect of the present invention, there is provided a base station in a telecommunications network, wherein the base station comprises means for performing power control by the method specified in the first aspect of the present invention.

According to a fourth aspect of the present invention, there is provided a telecommunications network comprising

means for performing power control by the method specified in the first aspect of the present invention.

It should be emphasised that the term

5 "comprises/comprising" when used in this specification is taken to specify the presence of stated features, integers, steps or components but does not preclude the presence or addition of one or more other features, integers, steps, components or groups thereof.

10

Brief Description of the Drawings

For a better understanding of the present invention, and to show how it may be put into effect, reference will now
15 be made, by way of example, to the accompanying drawings in which:

Figure 1 is a schematic diagram of the basic features in a radio telecommunications network;

20

Figure 2 shows a flow chart outlining a general outer loop power control algorithm;

Figure 3 shows a flow chart outlining use of an extended
25 outer loop power control algorithm in accordance with the present invention; and

Figure 4 is a schematic diagram of the network structure in accordance with the present invention.

30

Detailed Description of Embodiments

Where a telecommunications network has several channels in use, Radio Resources Management (RRM) implements an
35 extended outer loop power control algorithm. This algorithm functions to determine a single SIR reference

value suitable for all of the channels in use at one time. This is achieved by determining a separate used SIR reference value for each channel l , where $l=\{1, \dots, \text{number of channels in use}\}$. The initial step may
 5 be characterised as follows:

$$SIR_r(l,0) = \frac{1}{b_2} (\log_{10}(BLER_r(l)) - a_2)$$

In practice, a_2 could be 0.6 and b_2 could be -1.5.
 10 Clearly, this SIR reference is dependent upon the channel user's QoS requirements.

In order to update the SIR reference for each allotted channel at the following block, $k=1$, a quality assessment
 15 is performed on that channel (shown below using a CRC). The updating step may be characterised as follows:

$$20 \quad SIR_r(l, k+1) := \begin{cases} SIR_r(l, k) + SIR_{inc} & \text{if CRC}(l) \text{ not OK,} \\ SIR_r(l, k) - \frac{BLER_r(l)}{1 - BLER_r(l)} SIR_{inc} & \text{if CRC}(l) \text{ OK.} \end{cases}$$

where SIR_{inc} refers to an incremental increase in the SIR reference for channel l . SIR_{inc} is typically 0.3dB to
 25 1.0dB, and may be the same for all channels. In other words, where the received signal quality is better than the required signal quality, then the updated SIR reference value will be an incremental decrease. Where the received signal quality is worse than the required
 30 signal quality, then the updated SIR reference value will be an incremental increase.

The updated SIR reference value is compared with a predetermined minimum SIR reference value. Where the
 35 former is greater than the latter, then the updated SIR reference value is used. If the updated SIR reference

value calculated is below the predetermined minimum SIR reference value, the predetermined minimum SIR reference value is substituted for the updated SIR reference value. This comparison may be characterised as follows:

5

$$SIR_r(l, k+1) := \max(SIR_r(l, k+1), SIR_{min})$$

In order for the network to set an overall updated SIR reference value for all allotted channels the following equation applies:

10

$$SIR_r(k) = \max_l SIR_r(l, k)$$

All channels multiplexed on a common physical channel must use a common SIR reference value. Thus, the highest updated SIR reference value for all allotted channels for a particular block k , is used as the overall SIR reference value for the group of channels for that block.

The reason for setting a predetermined minimum SIR reference value for each channel is that, if this were not done, the calculated SIR reference value for a channel could reach very low values. This is the case if the channel achieves better QoS than requested for a long period of time. If the channel multiplexing situation changes, for instance when a new channel is dropped or added, or when the QoS parameters for a channel changes, the used SIR reference value may become insufficient to achieve accurate QoS for this channel. Without the predetermined minimum SIR reference value, it could take excessive time for the calculated updated SIR reference value to reach an acceptable level again.

Typically, setting SIR_{min} to -10dB will enable all allotted channels to regain control of the SIR reference

35

within a reasonable time (generally less than 1 second)
if the traffic situation changes.

In Figure 3, a RRM operates in step 30 to obtain an SIR
5 reference value for the initial block for the allotted
channel under consideration. A QoS assessment is
performed in step 32 by means of, for example, a CRC.
Where it is determined that the current quality is
acceptable, the SIR reference value is decremented in
10 step 34 resulting in an updated SIR reference value.
However, where the QoS is inadequate for user .
requirements the SIR reference value is incremented in
step 36 in order to achieve the updated SIR reference
value. A comparison is performed in step 38 to determine
15 whether the updated SIR reference value is greater than a
predetermined SIR minimum value. Thus, where the updated
SIR reference value is greater than the predetermined SIR
minimum value then the updated SIR reference value is
utilised in step 40 for the block and channel under
20 consideration. However, where the updated SIR reference
value is less than the predetermined SIR minimum value,
the predetermined SIR minimum value is utilised in step
42 instead of the updated SIR reference value.

25 It will be apparent to the skilled person that the outer
loop power control algorithm implemented on the channel
under consideration in Figure 3 can be implemented for
each of several further allotted channels within the
telecommunications network under the control of the RRM.

30 The SIR reference value to be used for each channel in
respect of the same block is compared in step 44 to
determine a maximum used SIR reference value, which value
is said to control the SIR reference value for the
telecommunications network. Thus, by use of the used SIR
35 reference values of the allotted channels the RRM is

implementing an extended outer loop power control algorithm in accordance with the present invention.

It is necessary for this process to be repeated for each of blocks $k=0, 1, 2, 3, \dots, n$, to ensure an acceptable QoS is provided even when the variables involved (such as number of allotted channels, maximum SIR reference value required, etc.) change.

- Thus, the SIR reference value is set for multiple transport channels and advantageously the complexity of the extended outer loop power control algorithm is very low.
- Figure 4 further illustrates the flow chart of Figure 3, showing the use of a common maximum used SIR reference value for multiple channels within a network. A first RMM 50, a second RMM 52 and a third RMM 54 each have two inputs. The single output 68 70 72 from the first, second and third controllers 50 52 54 are multiplexed onto a single physical channel 76 via a single comparison means 74.

- In operation, the first RMM 50 has two input signals, namely a first SIR reference value 56 and a first predetermined SIR minimum value 58. The second RMM 52 has two input signals, a second SIR reference value 60 and a second predetermined SIR minimum value 62. Similarly, the third RMM 54 has two input signals, a third SIR reference value 64 and a third predetermined SIR minimum value 66. Each RMM performs a QoS assessment and, dependent upon the result, increments or decrements the SIR reference value. Each RMM has a single output 68 70 72 comprising a used SIR value specific to that channel. The comparison means 74 functions to determine the maximum used SIR reference value from the first,

second and third used SIR values 68 70 72 input to the comparison means 74. This value is said to control the SIR reference value for the telecommunications network. The QoS assessment performed by each RRM implements an
5 extended outer loop power control algorithm in accordance with the present invention.

It will be apparent to the skilled person that the above specified algorithm is not exhaustive and variations may
10 be employed to achieve a similar result whilst employing the same inventive concept. For example, the extended outer loop power control algorithm can be implemented at a mobile station level, base station level or radio network controller level.

15 Furthermore, the skilled person will be aware that the present invention may be implemented in respect of any outer loop power control algorithm, such as the PI algorithm or the jump algorithm.

20 It can therefore be seen that the present invention provides power control in RRM which has significant advantages over the conventional systems.

25

30

35

CLAIMS

1. A method of power control in a mobile telecommunications network, the method comprising the steps of:
- calculating a signal strength reference value for each of a plurality of channels in use based on a previously calculated value for that channel;
- maintaining the calculated signal strength reference value for a channel at or above a predetermined minimum signal strength reference value; and
- determining a signal strength reference value to be used for all of said plurality of channels in use, as the highest of all of the calculated signal strength reference values.
2. The method as claimed in claim 1, wherein the signal strength reference value for a channel is a Signal-to-Interference Ratio (SIR) reference value.
3. The method as claimed in claim 1, further comprising incrementally increasing or decreasing the signal strength reference value dependent upon a quality criteria check.
4. The method as claimed in claims 2, wherein the step of calculating a SIR reference value for each of the plurality of channels in use is performed by applying the algorithm:

$$SIR_r(k) = kp * e(k) + ki * I(k)$$

where k denotes block number, $SIR_r(k)$ denotes the SIR reference for block k , kp and ki are parameters which control algorithm convergence speed and stability and

$$I(k+1) = I(k) + e(k).$$

5. The method as claimed in claim 4, wherein $e(k)$ takes different values dependent upon whether a predetermined quality criterion is met, such that:

5

$$\begin{aligned} e(k) &= -BLER_r, & \text{if quality criterion met,} \\ e(k) &= 1 - BLER_r, & \text{if quality criterion not met} \end{aligned}$$

10 where $BLER_r$ refers to the BLER reference.

6. The method as claimed in claim 4, wherein the parameters:

15

$$\begin{aligned} kp &= 0 \\ ki &= SIR_{inc} / (1 - BLER_r) \end{aligned}$$

are used, where SIR_{inc} refers to an incremental increase in the SIR reference.

20 7. The method as claimed in claims 2, 4, 5 and 6, wherein the step of maintaining the calculated signal strength reference value for a channel is determined via a Proportional Integral (PI) algorithm and characterised by:

25

$$SIR_r(l, k+1) := \begin{cases} SIR_r(l, k) + SIR_{inc} & \text{if quality criterion not met,} \\ SIR_r(l, k) - \frac{BLER_r(l)}{1 - BLER_r(l)} SIR_{inc} & \text{if quality criterion met.} \end{cases}$$

30 where $SIR_r(l, k)$ denotes the SIR reference for channel $l=1, \dots, N$ at block k . $BLER_r(l)$ refers to the BLER reference for channel l .

35 8. The method as claimed in claim 7, wherein the quality criterion check is based on a Bit Error Rate (BER) reference value.

9. The method as claimed in claim 7, wherein the quality criterion check is based on a Cyclic Redundancy Check (CRC) reference value.

5

10. The method as claimed in claim 7, comprising calculating an initial SIR reference value $SIR_r(1, 0)$ for each of the plurality of channels in use for an initial block $k=0$ as:

10

$$SIR_r(1,0) = \frac{1}{b_2} (\log_{10}(BLER_r(1)) - a_2)$$

where a_2 and b_2 are channel model parameters.

15 11. The method as claimed in claims 1 to 10, wherein the mobile telecommunications network uses WCDMA.

12. A mobile station for use in a telecommunications network, wherein the mobile station comprises means for performing power control by a method comprising:
20 calculating a signal strength reference value for each of a plurality of channels in use based on a previously calculated value for that channel;
maintaining the calculated signal strength reference
25 value for a channel at or above a predetermined minimum signal strength reference value; and
determining a signal strength reference value to be used for all of said plurality of channels in use, as the highest of all of the calculated signal strength
30 reference values.

13. The mobile station as claimed in claim 12, wherein the step of maintaining the calculated signal strength reference value for a channel is determined via a
35 Proportional Integral (PI) algorithm and characterised by:

$$SIR_r(l, k+1) := \begin{cases} SIR_r(l, k) + SIR_{inc} & \text{if quality criterion not met,} \\ SIR_r(l, k) - \frac{BLER_r(l)}{1 - BLER_r(l)} SIR_{inc} & \text{if quality criterion met.} \end{cases}$$

5

where $SIR_r(l, k)$ denotes the SIR reference for channel $l=1, \dots, N$ at block k . $BLER_r(l)$ refers to the BLER reference for channel l .

10 14. The mobile station as claimed in claims 12 and 13, wherein the mobile telecommunications network uses WCDMA.

15 15. A base station for use in a telecommunications network, wherein the base station comprises means for performing power control by a method comprising:
calculating a signal strength reference value for each of a plurality of channels in use based on a previously calculated value for that channel;
20 maintaining the calculated signal strength reference value for a channel at or above a predetermined minimum signal strength reference value; and
determining a signal strength reference value to be used for all of said plurality of channels in use, as the
25 highest of all of the calculated signal strength reference values.

16. The base station as claimed in claim 15, wherein the step of maintaining the calculated signal strength
30 reference value for a channel is determined via a Proportional Integral (PI) algorithm and characterised by:

$$35 \quad SIR_r(l, k+1) := \begin{cases} SIR_r(l, k) + SIR_{inc} & \text{if quality criterion not met,} \\ SIR_r(l, k) - \frac{BLER_r(l)}{1 - BLER_r(l)} SIR_{inc} & \text{if quality criterion met.} \end{cases}$$

where $SIR_r(l, k)$ denotes the SIR reference for channel $l=1, \dots, N$ at block k . $BLER_r(l)$ refers to the BLER reference for channel l .

5

17. The base station as claimed in claims 15 and 16, wherein the mobile telecommunications network uses WCDMA.

18. A telecommunications network, comprising means for
 10 performing power control by a method comprising:
 calculating a signal strength reference value for
 each of a plurality of channels in use based on a
 previously calculated value for that channel;
 maintaining the calculated signal strength reference
 15 value for a channel at or above a predetermined minimum
 signal strength reference value; and
 determining a signal strength reference value to be
 used for all of said plurality of channels in use, as the
 highest of all of the calculated signal strength
 20 reference values.

19. The telecommunications network as claimed in claim
 18, wherein the step of maintaining the calculated signal
 strength reference value for a channel is determined via
 25 a Proportional Integral (PI) algorithm and characterised
 by:

$$SIR_r(l, k+1) := \begin{cases} SIR_r(l, k) + SIR_{inc} & \text{if quality criterion not met,} \\ SIR_r(l, k) - \frac{BLER_r(l)}{1 - BLER_r(l)} SIR_{inc} & \text{if quality criterion met.} \end{cases}$$

30

where $SIR_r(l, k)$ denotes the SIR reference for channel $l=1, \dots, N$ at block k . $BLER_r(l)$ refers to the BLER reference for channel l .

35

20. The telecommunications network as claimed in claims 18 and 19, wherein the mobile telecommunications network uses WCDMA.

5

10

15


20

25

30

35

1/4



2/4




Figure 2

3/4




Figure 3

4/4




Figure 4

INTERNATIONAL SEARCH REPORT

International Application No

PCT/EP 03/09781

A. CLASSIFICATION OF SUBJECT MATTER
IPC 7 H04B7/005

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, COMPENDEX, INSPEC, PAJ, IBM-TDB, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 6 173 162 B1 (JOHANSSON MATHIAS ET AL) 9 January 2001 (2001-01-09) column 1, line 6 - line 8 column 1, line 36 - line 46 column 1, line 66 - column 2, line 3 column 2, line 32 - line 34 column 2, line 45 - line 49 column 3, line 4 - line 30 column 3, line 43 - line 47 column 3, line 60 - line 63 column 4, line 1 - line 15 column 6, line 66 - column 7, line 24 figures 3-7	1-3, 12, 15, 18
A	---	4-11, 13, 14, 17, 19, 20
	--- -/--	



Further documents are listed in the continuation of box C.



Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
- *&* document member of the same patent family

Date of the actual completion of the international search

19 December 2003

Date of mailing of the international search report

08/01/2004

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel (+31-70) 340-2040, Tx. 31 651 epo nl,
Fax (+31-70) 340-3016

Authorized officer

Schreib, F

INTERNATIONAL SEARCH REPORT

International Application No

PCT/EP 03/09781

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	EP 0 987 833 A (NIPPON ELECTRIC CO) 22 March 2000 (2000-03-22) abstract paragraphs '0001!', '0003!', '0004!', '0007!', '0008!', '0010!- '0013!', '0017!', '0020! figures 1,4-6	1-3, 12, 15, 18
A	----- EP 1 215 833 A (LUCENT TECHNOLOGIES INC) 19 June 2002 (2002-06-19) paragraph '0001! - paragraph '0028! figures 1,2	4-11, 13, 14, 17, 19, 20
A	----- US 5 991 284 A (WILLENEGGER SERGE ET AL) 23 November 1999 (1999-11-23) column 1, line 5 -column 4, line 64 figure 2 -----	1-20

INTERNATIONAL SEARCH REPORT

International Application No.

PCT/EP 03/09781

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 6173162	B1	09-01-2001	AU 746139 B2 18-04-2002
			AU 8050198 A 04-01-1999
			CN 1113483 B 02-07-2003
			EP 0990314 A1 05-04-2000
			JP 2002503427 T 29-01-2002
			WO 9858461 A1 23-12-1998
			TW 379486 B 11-01-2000
EP 0987833	A	22-03-2000	JP 3199238 B2 13-08-2001
			JP 2000102052 A 07-04-2000
			CN 1249653 A 05-04-2000
			EP 0987833 A2 22-03-2000
			US 6285887 B1 04-09-2001
EP 1215833	A	19-06-2002	EP 1215833 A1 19-06-2002
			US 2002115443 A1 22-08-2002
US 5991284	A	23-11-1999	AU 6277898 A 08-09-1998
			CN 1307758 T 08-08-2001
			EP 1016299 A1 05-07-2000
			JP 2002501689 T 15-01-2002
			WO 9836606 A2 20-08-1998
			US 6240071 B1 29-05-2001
			US 2001010684 A1 02-08-2001